

Installation Manual



Optional Applications Software on Windows-Based Oscilloscopes

077-0067-04

www.tektronix.com


077006704

Copyright © Tektronix. All rights reserved. Licensed software products are owned by Tektronix or its suppliers and are protected by United States copyright laws and international treaty provisions.

Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supercedes that in all previously published material. Specifications and price change privileges reserved.

TEKTRONIX, TEK, and RT-EYE are registered trademarks, and SignalVu is a trademark of Tektronix, Inc.

Windows, Windows 98, Windows NT, Windows 2000, Windows XP Professional and Windows Me are trademarks of Microsoft Corporation.

Contacting Tektronix

Tektronix, Inc.
14200 SW Karl Braun Drive
P.O. Box 500
Beaverton, OR 97077
USA

For product information, sales, service, and technical support:

- In North America, call 1-800-833-9200.
- Worldwide, visit www.tektronix.com to find contacts in your area.

WARRANTY 9(b)

Tektronix warrants that the media on which this software product is furnished and the encoding of the programs on the media will be free from defects in materials and workmanship for a period of three (3) months from the date of shipment. If any such medium or encoding proves defective during the warranty period, Tektronix will provide a replacement in exchange for the defective medium. Except as to the media on which this software product is furnished, this software product is provided "as is" without warranty of any kind, either express or implied. Tektronix does not warrant that the functions contained in this software product will meet Customer's requirements or that the operation of the programs will be uninterrupted or error-free.

In order to obtain service under this warranty, Customer must notify Tektronix of the defect before the expiration of the warranty period. If Tektronix is unable to provide a replacement that is free from defects in materials and workmanship within a reasonable time thereafter, Customer may terminate the license for this software product and return this software product and any associated materials for credit or refund.

THIS WARRANTY IS GIVEN BY TEKTRONIX WITH RESPECT TO THE PRODUCT IN LIEU OF ANY OTHER WARRANTIES, EXPRESS OR IMPLIED. TEKTRONIX AND ITS VENDORS DISCLAIM ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. TEKTRONIX' RESPONSIBILITY TO REPLACE DEFECTIVE MEDIA OR REFUND CUSTOMER'S PAYMENT IS THE SOLE AND EXCLUSIVE REMEDY PROVIDED TO THE CUSTOMER FOR BREACH OF THIS WARRANTY. TEKTRONIX AND ITS VENDORS WILL NOT BE LIABLE FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES IRRESPECTIVE OF WHETHER TEKTRONIX OR THE VENDOR HAS ADVANCE NOTICE OF THE POSSIBILITY OF SUCH DAMAGES.

Table of Contents

Preface	ii
Free Trial	ii
Product Description	1
Application and Oscilloscope Compatibility	1
Application Installation	13
Installing Adobe Reader	13
Reinstalling an Application	13
Installing an Application	15
Installing Report Generator	16
Applying a New Label	17
Enabling an Application	17
Starting an Application	18
Downloading Applications Through the Web Site	18

Preface

You can use information in this manual to install any application from the *Optional Applications Software for Windows-Based Oscilloscopes DVD* onto your Microsoft Windows-based Tektronix oscilloscope. For compatibility information, refer to the table on page 2.

Free Trial

A free trial is available for applications on supported oscilloscopes listed in the table on page 2. These applications were installed on the supported instrument at the factory. You can start and exit an application to help you evaluate Tektronix software solutions. After the free trials, you must purchase an option installation key to continue to use the application.

NOTE. *If a new application becomes available, or a new version of an existing application is released, you can download the application as described on page 18 to begin your free trials.*

NOTE. *For the DPOJET and DPOPWR applications, each free trial lasts until the oscilloscope application is restarted. Unlike other applications, you can return to DPOJET or DPOPWR any number of times on a single free trial as long as the TekScope application remains open.*

Product Description

Tektronix provides many applications for Microsoft Windows-based oscilloscopes that you can use to test, analyze, and debug various types of electronic devices and products. To learn about most applications, you can browse the documentation folder on the *Optional Applications Software on Windows-Based Oscilloscopes DVD*, and view any document listed. You can also check www.tektronix.com for application notes on how to resolve complex problems, such as how to analyze jitter or how to verify compliance to a serial data standard.

Tektronix recommends that you upgrade your oscilloscope to the latest firmware before installing or operating an application. You can download the latest firmware from www.tektronix.com. Be sure to select the firmware version appropriate for your specific oscilloscope model.

NOTE. *Be sure to install the oscilloscope firmware before you install any optional application software.*

Application and Oscilloscope Compatibility

The next table lists the applications included on the optional applications DVD with the compatible oscilloscope models and firmware version numbers.

NOTE. *To display the firmware version number of the oscilloscope, select Help > About TekScope... in the menu bar of the TekScope window.*

For updates on the applications that are not available on the DVD, go to www.tektronix.com/software.

For those applications that use the Report Generator, it is installed automatically when the application is installed using the optional applications DVD. To install the Report Generator manually, refer to page 16. To install an application, refer to page 15.

Applications and compatible oscilloscopes

Application name	Software version	Oscilloscope model	Recommended firmware version
DPOJET Jitter and Eye Diagram Analysis Tools - Essentials	V 2.1.1 and above	DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
DPOJET Jitter and Eye Diagram Analysis Tools - Advanced			
DDR Analysis	V2.1.1 and above	DPO7254, DPO7354, DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
PCI-Express	V 2.1.1 and above	DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
TDSCPM2 Communications Pulse Analysis*	V 3.0.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		TDS5032B, TDS5034B, TDS5052B, TDS5054B, TDS5054BE, TDS5104B	V 2.0.11 and above
		TDS7054, TDS7104	V 2.5.5 and above
		CSA7154, CSA7404, TDS7154, TDS7254, TDS7404	V 2.5.3 and above
		DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
TDSDDM2 Disk Drive Analysis	V 3.0.1 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		TDS5034, TDS5052, TDS5054, TDS5104	V 1.2.1 and above
		TDS5034B, TDS5052B, TDS5054B, TDS5054BE, TDS5104B	V 2.0.11 and above
		TDS7054, TDS7104	V 2.5.5 and above
		CSA7154, CSA7404, TDS7154, TDS7254, TDS7404	V 2.5.3 and above
		DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
TDS DVI Compliance Tools	V 3.0.6 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		CSA7404, TDS7254, TDS7404, TDS6404, TDS6604	V 2.5.3 and above
		DPO7354, DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
TDSSET3 Ethernet Compliance Tools	V 3.1.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		TDS5052B, TDS5054B, TDS5104B, TDS5032B, TDS5034B	V 2.0.11 and above
		TDS7054, TDS7104	V 2.5.5 and above
		CSA7154, CSA7404, TDS6404, TDS6604, TDS7154, TDS7404, TDS7254	V 2.5.3 and above
		DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
TDSHT3 V1.2a HDMI Compliance Tools	V 3.0.2 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		CSA7404, TDS7254, TDS7404	V 2.5.3 and above
		DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
TDSHT3 V1.3 HDMI Compliance Tools	V 4.0.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7404B, TDS7704B	V 5.1.3 and above
		CSA7404, TDS7404	V 2.5.3 and above
		DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
DTG Pattern Files	V 3.3.2 and above	DTG5334	V 2.1.1 and above
TDSJIT3V2A Jitter and Timing Analysis (Advanced) and TDSJIT3V2E Jitter and Timing Analysis (Essentials)	V 3.0.2 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		TDS5034B, TDS5054B, TDS5054BE, TDS5104B	V 2.0.11 and above
		TDS7054, TDS7104	V 2.5.5 and above
		CSA7154, CSA7404, TDS6404, TDS6604, TDS7154, TDS7254, TDS7404	V 2.5.3 and above
		TDS5034, TDS5054, TDS5104	V 1.2.1 and above
		DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
DPOPWR Power Analysis	V 1.0.6 and above	DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
RT-Eye Eye Analysis and Compliance Tools [†]	V 3.1.1 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		CSA7154, CSA7404, TDS6404, TDS6604, TDS7154, TDS7254, TDS7404	V 2.5.3 and above
		DPO7254, DPO7354, DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
FB-DIMM Compliance Module (requires RT-Eye application)	V 3.1.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		TDS7704B	V 5.1.3 and above
		TDS6604	V 2.5.3 and above
		DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
SATA and SAS Test Modules [†] (requires RT-Eye application)	V 3.1.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		TDS7704B	V 5.1.3 and above
		TDS6604	V 2.5.3 and above
		DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
InfiniBand Compliance Module [†] (requires RT-Eye application)	V 3.1.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7404B, TDS7704B	V 5.1.3 and above
		CSA7404, TDS6404, TDS6604, TDS7404	V 2.5.3 and above
		DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
PCI Express Compliance Module [†] (requires RT-Eye ap- plication)	V 3.1.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7404B, TDS7704B	V 5.1.3 and above
		CSA7404, TDS6404, TDS6604, TDS7404	V 2.5.3 and above
		DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
TDSUSB2 USB 2.0 Compliance Tools	V 3.3.0 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		TDS5034B, TDS5054B, TDS5104B	V 2.0.11 and above
		TDS7054, TDS7104	V 2.5.5 and above
		CSA7154, CSA7404, TDS6404, TDS6604, TDS7154, TDS7254, TDS7404	V 2.5.3 and above
		TDS5034, TDS5054, TDS5104	V 1.2.1 and above
		DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
TDSPTD Protocol Trigger and Decode	V 3.1.1 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		DPO7254, DPO7354, DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
TDSVNM CAN/LIN Analysis and Protocol Decode	V 3.0.4 and above	TDS5032B, TDS5034B, TDS5052B, TDS5054B, TDS5054BE, TDS5104B	V 2.0.11 and above
		TDS7054 [§] , TDS7104 [§]	V 2.5.5 and above
		TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
TekUWB Ultra Wideband Spectral Analysis	V 2.2.1 and above	TDS7704B	V 5.1.3 and above
		TDS6804B	V 5.1.2 and above
		TDS6124C, TDS6154C	V 5.1.5 and above
		DPO7254, DPO7354, DPO7404, DPO70404, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes (Cont.)

Application name	Software version	Oscilloscope model	Recommended firmware version
Report Generator [‡]	V 3.1.3 and above	TDS6124C, TDS6154C	V 5.1.5 and above
		TDS6604B, TDS6804B	V 5.1.2 and above
		CSA7404B, TDS7154B, TDS7254B, TDS7404B, TDS7704B	V 5.1.3 and above
		TDS5052B, TDS5054B, TDS5104B, TDS5034B, TDS5032B	V 2.0.11 and above
		TDS6604, TDS6404	V 2.5.3 and above
		TDS7054, TDS7104	V 2.5.5 and above
		CSA7154, CSA7404, TDS6404, TDS6604, TDS7154, TDS7404	V 2.5.3 and above
		DPO7054, DPO7104, DPO7254, DPO7354, DPO70404/B, DPO70604/B, DPO70804/B, DSA70404/B, DSA70604/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above
DPODSPT DisplayPort TX Compliance	V 1.1.20 and above	DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B	V 4.3.0 and above

Applications and compatible oscilloscopes

Application name	Software version	Oscilloscope model	Recommended firmware version
SignalVu Vector Signal Analysis	V 1.3.576 and above	DPO7054, DPO71604, DPO7104, DPO72004, DPO7254, DSA70404, DPO7354, DSA70604, DPO70404, DSA70804, DPO70604, DSA71254, DPO70804, DSA71604, DPO71254, DSA72004	V 4.2.2 and above
SDLA Serial Data Link Analysis**	V 1.0.0	DPO70404/B, DSA70404/B, DPO70604/B, DSA70604/B, DPO70804/B, DSA70804/B, DPO71254/B, DSA71254/B, DPO71604/B, DSA71604/B, DPO72004/B, DSA72004/B,	V 4.3.0 and above

* Oscilloscope (except CSA7000/B models, DPO7000, DPO/DSA70000 series, and DPO/DSA70000B series) requires Option SM, serial masks.

† Requires Windows 2000 or Windows XP operating system.

‡ Does not require an Option Installation Key or the JRE software.

§ Requires Windows 2000.

** Option DJA is not required, but if used with the SDLA application, option DJA needs to be V 1.2.1 and above. SDLA software cannot run concurrently with other applications (for example, JIT3v2 or TDSRT-Eye software) that use VISA to access the base oscilloscope. SDLA software is fully compatible with DPOJET software.

Application Installation

NOTE. Some applications may require a deskew fixture or a test fixture. The application online help includes connection procedures for these fixtures.

Installing Adobe Reader

NOTE. To view the documentation that comes with the *Optional Applications Software on Windows-Based Oscilloscopes DVD*, your system must have Adobe Reader installed.

There are two methods to install Adobe Reader:

- Insert the DVD into the system drive and allow the DVD Browser to auto-start. This process checks for the Adobe Reader and lets you know if you should upgrade or install Adobe Reader.
- If you close the DVD Browser or exit the installer early, you can always access the DVD contents directly. Go to the DVD drive and double-click on the Launch.exe file. This will launch the DVD Browser. There is an Adobe Reader link on the browser home page. You can use this link to install the Adobe Reader.

Reinstalling an Application

Most applications are factory installed on the hard disk in the oscilloscope at the time the oscilloscope is shipped. The DVD serves as a backup in case you have to rebuild the hard disk. The *Optional Applications Software on Windows-Based Oscilloscopes DVD* may contain applications that were introduced after you received your oscilloscope.

The optional applications DVD may contain a newer version of the application software than the version on your oscilloscope. (The latest versions can be found at www.tektronix.com/software)

Before you continue, determine if you need to install a newer version of the application. To do this, follow these steps:

1. In the menu bar of the TekScope window, select File > Run Application > <application name>

or App > <application name> or Analyze > <application name> as appropriate for your oscilloscope.

2. In the menu bar of the application, select Help > About <application> to display the software version number.
3. Check the version number of the application on the Tektronix Web site. To do so, follow these steps:
 - a. Access www.tektronix.com and select Software Downloads.

The Software Downloads page appears. To define the search criteria, use one of the following methods:

- Make selections in the Browse by category Products fields.
 - Enter information in the Search by keyword field. For example, Search by keyword TDSHT3.
- b. Select Go. The search returns a list of software.
 - c. Scroll through the list to the desired application, select the link, and view the Web page instructions to download the application to your oscilloscope. The version number is at the top of the Web page.

If the version number is higher than the version number in the compatibility table (on page 2), then follow the *Downloading Applications Through the Web Site* procedures on page 18.

The following table shows an example of how to check the application version numbers and determine whether you need to upgrade the application.

Checking the application software version number example

Application on the oscilloscope	As listed in the table on page 2	As shown on the Web site	Reinstall?
V 1.0.0	V 1.0.0	V 1.0.0	No
V 1.0.0	V 1.1.0	V 1.1.0	Yes, from the DVD or the Web site
V 1.0.0	V 1.1.0	V 1.2.0	Yes, from the Web site

Installing an Application

Normally, application software resides on the hard disk of your oscilloscope. However, you may need to install the application software for the following reasons:

- You receive an application that was introduced after you received your oscilloscope.
- You have to rebuild the hard disk of the oscilloscope.
- You download an update for an application from the Tektronix Web site.

The table on page 2 lists the available applications, compatible oscilloscope models, and the corresponding software version and firmware version numbers.

NOTE. *If access is denied when you install an application software on Windows 2000 or Windows XP operating systems, try logging in as an administrator.*

The installation procedure may require a mouse attached to the oscilloscope.

Restart the oscilloscope after uninstalling and start the installation again.

Application Introduced After you Received an Oscilloscope. To install an application that does not currently reside on the hard disk of the oscilloscope from the optional applications DVD, follow these steps:

1. Insert the optional applications DVD in the DVD drive.
2. If the oscilloscope does not automatically start the Installation Browser program, follow these steps:
 - a. Select and open the **My Computer** icon.
 - b. In the Exploring - My Computer window, select the drive used in step 1 and then open the Launch.exe file.
3. Select the appropriate button for the application that you want to install.
4. Follow the on-screen instructions given by the Installation Wizard. Answer “OK” if prompted to install the JRE (Java Runtime Environment) software and accept all defaults.
5. Reboot the oscilloscope to complete the installation.

NOTE. When you install a newer version of software, the existing version is uninstalled as part of the installation procedure.

If you install a new version of an enabled application, you do not have to enter the authorized option installation key again.

Installing Report Generator

To install Report Generator from the optional applications DVD, follow these steps:

1. Insert the optional applications DVD in the DVD drive.
2. If the oscilloscope does not automatically start the Installation Browser program, follow these steps:
 - a. Select and open the **My Computer** icon.
 - b. In the Exploring - My Computer window, select the drive used in step 1 and then open the Launch.exe file.
3. Select the Tektronix Report Generator button to install.

4. Follow the on-screen instructions given by the Installation Wizard.

NOTE. *If the same version of the Report Generator already exists, a Modify/Repair or Remove option is displayed in a dialog box. Select the Modify/Repair option and follow the on-screen instructions to install the Report Generator.*

Applying a New Label

You need to attach a label to your oscilloscope rear panel if you do any of the following:

- Purchase a software license for an application already installed on the oscilloscope; the license allows you to enable the application
- Upgrade the licensed application to a newer version
- Purchase an application that was introduced after you received your oscilloscope

The label comes in the package with the activation key. The label contains important information, such as the serial number of the oscilloscope, options purchased for that serial number, and an authorized option installation key number. Since each label is unique, apply the new label over the existing one.

Enabling an Application

You must enter the authorized option installation key to enable all purchased applications and product options on your oscilloscope. The key is unique; it is specific to the serial number of the oscilloscope and purchased options.

Follow these steps to enter your alphanumeric key number:

1. Power on the oscilloscope and set it to the menu-bar mode.
2. Go to the Utilities menu in the menu bar and select Option Installation.
3. Follow the on-screen instructions to enter the alphanumeric key number exactly as it is printed on the rear-panel label.

Starting an Application

To start an application, select File > Run > <application name>, App > <application name>, or Analyze > <application name> in the menu bar of the TekScope window. Some applications can also be started from the desktop. After loading the application, check for a shortcut application icon on the desktop.

After installation, the user manuals and the application are available on the oscilloscope from Start Menu > Programs > TekApplications.

Downloading Applications Through the Web Site

You can find information about applications and firmware for your oscilloscope at www.tektronix.com/software. You can download updates to the software and other free applications.

NOTE. *When you update an application, the Release Notes file from www.tektronix.com replaces the Readme.txt file in the Web download self extracting.exe file.*

To download an application to your oscilloscope or personal computer, follow these steps:

1. Go to www.tektronix.com/software.

Use one of the following methods to define the search criteria:

- Select Products and then Oscilloscopes in the Browse by category fields.
- Enter information in the Search by keyword field. For example, Search by keyword TDSUSB2.

2. Select Go. The search returns a list of software.
3. Browse to and select the link for your software.

Notice that the software link you selected includes other links to view the Installation Instructions and the Release notes, plus the version number of the application at the top of the page.

4. Click the Download File button. A MyTek Profile appears.
 - a. Log on to your MyTek Profile or create a new profile. When finished, a File Download dialog box appears.

- b.** Select Save on the File Download dialog box, and then specify a location to save the .exe file, such as your personal computer or oscilloscope desktop.

If you save the downloaded file to your personal computer, you may want to copy this file to a DVD media, a CD-ROM or a USB flash drive to transfer it to your oscilloscope.

- 5.** To start the installation, open the downloaded file and follow the on-screen prompts. To complete the installation, reboot your instrument.

